

LED CORN LIGHT SERIES - 2ND GEN

FEATURES

- Environmentally friendly; free of mercury, UV and IR emissions
- 360 degree beam angle
- Replaces traditional HPS and HID lamps
- 80% energy savings
- Instant-on (No delay)
- UL & DLC listed
- Suitable for damp locations
- Five-year warranty

*DLC Certification applies to:
RCN080H0202, RCN080H0203, RCN100H0202,
RCN100H0203, RCN120H0202, RCN120H0203,
RCN150H0202, RCN150H0203



APPLICATION


Post Top Lights, High Bays, Recessed Lighting, Shoebox Lights

SA : STOCK AVAILABLE/NO BACKORDERS

INV: INVENTORY

INV/MTO-qty: INVENTORY/MTO WHEN STOCK DEPLETED

MTO-qty: MADE TO ORDER



Technical Specification

Part No.	Watt. (W)	Lumens (lm)	CCT(K)	Base	HID/CFL Equiv.	DLC	Live Status
RCN015H0201	15	1380	3000	E26	75/45	N/A	SA
RCN015H0202	15	1380	4000	E26	75/45	N/A	SA
RCN015H0204	15	1425	6000	E26	75/45	N/A	SA
RCN020H0201	20	1840	3000	E26	100/70	N/A	SA
RCN020H0202	20	1840	4000	E26	100/70	N/A	SA
RCN020H0204	20	1900	6000	E26	100/70	N/A	SA
RCN030H0201	30	2760	3000	E26	125/105	N/A	SA
RCN030H0202	30	2760	4000	E26	125/105	N/A	SA
RCN030H0203	30	2850	5000	E26	125/105	N/A	SA
RCN030H0204	30	2850	6000	E26	125/105	N/A	SA
RCN030H0206	30	2760	3000	E39	125/105	N/A	SA
RCN030H0207	30	2760	4000	E39	125/105	N/A	SA
RCN030H0208	30	2850	5000	E39	125/105	N/A	SA
RCN030H0209	30	2850	6000	E39	125/105	N/A	SA
RCN040H0201	40	3680	3000	E26	150/105	N/A	SA
RCN040H0202	40	3680	4000	E26	150/105	N/A	SA
RCN040H0204	40	3800	6000	E26	150/105	N/A	SA
RCN040H0206	40	3680	3000	E39	150/105	N/A	SA
RCN040H0207	40	3680	4000	E39	150/105	N/A	SA
RCN040H0208	40	3800	5000	E39	150/105	N/A	SA
RCN040H0209	40	3800	6000	E39	150/105	N/A	SA
RCN060H0201	60	5520	3000	E26	175/150	N/A	SA
RCN060H0203	60	5700	5000	E26	175/150	N/A	SA
RCN060H0204	60	5700	6000	E26	175/150	N/A	SA
RCN060H0206	60	5520	3000	E39	175/150	N/A	SA
RCN060H0207	60	5520	4000	E39	175/150	N/A	SA
RCN060H0208	60	5700	5000	E39	175/150	N/A	SA

The Replacement information listed is provided to help inform users of the various assumptions, factors, and methods involved when making lighting replacement decisions, and is for general information purposes only. ReneSola America disclaims all responsibility for any outcomes resulting from the use of this tool. Any reliance you place on this tool is therefore strictly at your own risk.